

AirMagnet Pocket PC Compatibility Matrix - August 2003

Minimum System Requirements

- Pocket PC 2002 Operating System (AirMagnet Is Compatible With Pocket PC 2003)
- Strong ARM processor/Xscale based hardware system
- 32 MB Memory Minimum (64 MB Recommended)
- 2 MB Free File Space for Installation
- 8 MB Free Memory Space
- Open Slot for PCMCIA card or CF Type II Card

Pocket PCs conforming to these minimum requirements should be able to run AirMagnet software without issue. However, not every model of Pocket PC on the market has been tested by AirMagnet. For a list of Pocket PCs that have been verified compatible by AirMagnet, please refer to the "Verified Pocket PCs" section below.

Verified Pocket PCs

Model	ROM	RAM	Processor	Availability	PC Card Expansion	Battery for Expansion Packs	Verified Compatible?
HP iPAQ Pocket PC H2215	56	64	400 MHz, Intel Xscale	America, Europe	NA	NA	Verified using AirMagnet Proxim CF Type II Card.

HP iPAQ Pocket PC H5450/H5455	48	64	400 MHz, Intel Xscale	America, Europe		249708-B21 PC Card Expansion Pack Plus (Single w/ removable Battery) 216198-B21 Dual-Slot PC Card Expansion Pack. Expansion Pack Battery 253512-B21 Slim 253514-B21 Extended	Verified using AirMagnet Proxim PC Card and AirMagnet Cisco PC Card
HP iPAQ 5555 Pocket PC	48	128	400 MHz, Intel Xscale	America, Europe	Supports PC Card Expansion, CF Expansion, Integrated SD slot, SDIO ready		Verified using AirMagnet Proxim PC Card and AirMagnet Cisco PC Card
Compaq iPAQ Pocket PC H3760/H3765	32	64	206 MHz, Intel StrongARM	America, Europe, Asia Pacific, Latin America	249708-B21 PC Card Expansion Pack Plus (Single w/ removable Battery) 216198-B21 Dual-Slot PC Card Expansion Pack	Expansion Pack Battery 253512-B21 Slim 253514-B21 Extended	Verified using AirMagnet Proxim PC Card and AirMagnet Cisco PC Card.
Compaq iPAQ Pocket PC H3870/H3850/3830 hp iPAQ H3835	32	64, 32 for 3830	206 MHz, Intel StrongARM	America, Europe, Asia Pacific, Latin America	249708-B21 PC Card Expansion Pack Plus (Single w/ removable Battery) 216198-B21 Dual-Slot PC Card Expansion Pack	Expansion Pack Battery 253512-B21 Slim 253514-B21 Extended	Verified using AirMagnet Proxim PC Card and AirMagnet Cisco PC Card.

Compaq H3970/H3950 hp iPAQ H3975/H3955	48	64	400 MHz, Intel Xscale	America, Europe, Asia Pacific, Latin America	249708-B21 PC Card Expansion Pack Plus (Single w/ removable Battery) 216198-B21 Dual-Slot PC Card Expansion Pack	Expansion Pack Battery 253512-B21 Slim 253514-B21 Extended	Verified using AirMagnet Proxim PC Card and AirMagnet Cisco PC Card.
HP iPAQ 5150 Pocket PC	32	64	400 MHz PXA255 Xscale	America, Europe, Asia Pacific, Latin America	249708-B21 PC Card Expansion Pack Plus (Single w/ removable Battery) 216198-B21 Dual-Slot PC Card Expansion Pack	Expansion Pack Battery 253512-B21 Slim 253514-B21 Extended	Verified using AirMagnet Proxim PC Card and AirMagnet Cisco PC Card.
HP Jornada 560 Series	32	32/64	206 MHz, Intel StrongARM	Worldwide	HP F2912A CompactFlash Type Ie to PC card sleeve with MMC slot	N/A	Verified using AirMagnet Proxim PC Card and AirMagnet Cisco PC Card.
Toshiba e570/e550g	32	64	206 MHz, Intel StrongARM	United States, United Kingdom, Germany, France	No Expansion Packs for PC Cards. Must use AirMagnet CF Type II card	N/A	Verified using AirMagnet Proxim CF Type II Card.
Toshiba e750	32	64	Intel PXA255 processor, 400 MHz	United States, United Kingdom, Germany, France	NA	NA	Verified using AirMagnet Proxim CF Type II Card.

Dell Axim X5	32/48	32/64	300,400 MHz, Intel Xscale	United States and Canada	No Expansion Packs for PC Cards. Must use AirMagnet CF Type II card	N/A	Not-Verified, Specs indicate it should be compatible when used with AirMagnet Proxim CF type II card
Casio E-200	32	64	206 MHz, Intel StrongARM	Worldwide	JK-864PU PC Card Unit with USB port	N/A	Verified using AirMagnet Cisco PC Card when coupled to PC Card Unit. Note Casio's PC card unit will not work with AirMagnet Proxim PC Card due to voltage requirements.
NEC MobilePro P300	32	32	206 MHz, Intel StrongARM	United States, Europe, Japan	MC/PG-JK01 PC Card Expansion Jacket	N/A	Not-Verified, Specs indicate it should be compatible when coupled with PC Expansion and AirMagnet Proxim PC Card or AirMagnet Cisco PC Card
Fujitsu-Siemens Pocket LOOX	32	64	400 MHz, Intel Xscale	Europe, Japan	No Expansion Packs for PC Cards available. Must use AirMagnet CF Type II Card	N/A	Not-Verified, Specs indicate it should be compatible when used with AirMagnet Proxim CF type II card.

Audiovox Maestro PDA 1032	32	32	206 MHz, Intel StrongARM	United States	No Expansion Packs for PC Cards. Must use AirMagnet CF Type II card	N/A	Not-Verified, Specs indicate it should be compatible when used with AirMagnet Proxim CF type II card.
Zayo A600PPC/A600EXE	32	64	400 MHz, Intel Xscale	Worldwide. Zayo in United States, MyPal in Asia and Europe	Optional CF Expansion Pack Available, CF to PCMCIA extender also available	N/A	Not-Verified, Specs indicate it should be compatible when coupled with PC Expansion and AirMagnet Proxim PC Card or AirMagnet Cisco PC Card
Alaska Cove Mexmal	32	32	206 MHz, Intel StrongARM	Mexico	No Expansion Packs for PC Cards. Must use AirMagnet CF Type II card	N/A	Not-Verified, Specs indicate it should be compatible when used with AirMagnet Proxim CF type II card.